



DYNAMIC 620 START 230V 12-24V



Overview

DYNAMIC 620 START 230V 12-24V

cod. 829384

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans and light trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- display of charging and starting current
- protection against overloads and polarity reversal.

Technical data

CODE	CODE 829384	A_{EFF}	EFFECTIVE CHARGING CURRENT 90 A		ADJUSTMENT POSITIONS 4
V_{1PH}	SINGLE PHASE MAINS VOLTAGE 230 V	A_{EN}	RATED CHARGE CURR. EN60335-2-29 70 A		DIMENSIONS 36,5 - 46 - 75,5 cm
F	MAINS FREQUENCY 50 / 60 Hz	A_{1V/C}	START CURRENT 1V/C EN60335-2-29 360 A		WEIGHT 24 kg
P_{CHARGE}	CHARGE POWER 2 KW	A_{START MAX}	MAX STARTING CURRENT 570 A	BAR CODE	EAN CODE 800489773286 2
P_{START}	START POWER 10 KW	C_{MIN}	MIN. RATED REFERENCE CAPACITY 20 Ah		PIECES/PALLET 9 pz/pallet
	CHARGING VOLTAGE 12 / 24 V	C_{MAX}	MAX RATED REFERENCE CAPACITY 1550 Ah		PIECES/PALLET - B 6 pz/pallet - B