

C20 - Nato

PROCAP BOOSTER

12V
24V



Our BATTERYLESS PROCAP range uses the highest quality and most powerful UltraCapacitor technology to produce an extremely powerful booster fit for the toughest starting applications. Their light weight and ultra fast recharge allow professionals to perform an unlimited number of daily starts.

EXTERNAL CONNECTOR

An Anderson connector socket is fitted to the back of the unit allowing users to connect a number of industry starting connectors to the unit

12-24V SWITCH

Easy to use switch allows the booster to be changed from 12V to 24V.

LED CHARGE INDICATOR

The test button allows users to easily check the charge level of the booster and test the alternator of a vehicle.

REVERSE POLARITY ALARM

This audible and visual alert informs professionals of incorrect terminal connections.



Model
C20-Nato

Volts
12/24V

Peak Amps (A)
10500

Of Batteries
0

Location of Fuse
housing

Fuse (A)
1000

Dimensions (cm)
41x39x16

Cable Ø (mm2)
50

Cable length (cm)
176

Unit Weight (KG)
22.5

Charger Voltage (V)
14.4

Charger Amps (A)
3

Vehicle types



NATO CONNECTOR*

2 Meters Length (*In option)



LEMANIAENERGY
Switzerland

www.lemania-energy.com